MMX-4X4VWMV Tesira Command Sheet

For Tesira Command String blocks · Version 1.0.5

Every command the MMX-4X4VWMV takes over the network, as fixed strings for Tesira Command String blocks. The unit is controlled on its own control port (TCP 8000); no other KanexPro software is needed. The same strings, with their bytes, are in `KanexPro-MMX-4X4VWMV-Tesira-Command-Sheet-1.0.5.csv` for copying.

> **Before you start —** the Tesira server must reach the MMX-4X4VWMV on TCP port 8000. Give the unit a fixed IP address (or a DHCP reservation).

TABLE OF CONTENTS

1. Connection
2. Using the strings
3. Commands
4. Reading the unit back
5. Troubleshooting

1. CONNECTION

HOW THE UNIT IS CONTROLLED	
Transport	TCP, port 8000 (the unit's control port)
Line ending	"!" (hex `21`), after every string
Pacing	One string at a time. The unit answers within about 1.5 s; wait for the answer before the next string.
A refused string	The unit answers with an error line.

2. USING THE STRINGS

1. Point the Command String block at the unit's IP address, TCP port 8000.
2. Add one command per row of section 3: its string, then the line ending (hex `21`).
3. Wire each command to the control that should send it. The Bytes column is the whole string as it goes on the wire, to compare with a network capture.

Settings that only the unit's own web page has (its network, logins and firmware) stay on that page.

3. COMMANDS

92 strings.

#	Command	String	Bytes (hex, with the line ending)
1	**Mode: How the outputs are used = Matrix**	`s display mode 0`	`73 20 64 69 73 70 6C 61 79 20 6D 6F 64 65 20 30 21`
2	**Mode: How the outputs are used = Video wall**	`s display mode 1`	`73 20 64 69 73 70 6C 61 79 20 6D 6F 64 65 20 31 21`
3	**Mode: How the outputs are used = Multiview**	`s display mode 2`	`73 20 64 69 73 70 6C 61 79 20 6D 6F 64 65 20 32 21`
4	**Route: All outputs: Source = Input 1**	`s output 0 in source 1`	`73 20 6F 75 74 70 75 74 20 30 20 69 6E 20 73 6F 75 72 63 65 20 31 21`
5	**Route: All outputs: Source = Input 2**	`s output 0 in source 2`	`73 20 6F 75 74 70 75 74 20 30 20 69 6E 20 73 6F 75 72 63 65 20 32 21`
6	**Route: All outputs: Source = Input 3**	`s output 0 in source 3`	`73 20 6F 75 74 70 75 74 20 30 20 69 6E 20 73 6F 75 72 63 65 20 33 21`

7	Route: All outputs: Source = Input 4	`s output 0 in source 4`	`73 20 6F 75 74 70 75 74 20 30 20 69 6E 20 73 6F 75 72 63 65 20 34 21`
8	Route: Output 1: Source = Input 1	`s output 1 in source 1`	`73 20 6F 75 74 70 75 74 20 31 20 69 6E 20 73 6F 75 72 63 65 20 31 21`
9	Route: Output 1: Source = Input 2	`s output 1 in source 2`	`73 20 6F 75 74 70 75 74 20 31 20 69 6E 20 73 6F 75 72 63 65 20 32 21`
10	Route: Output 1: Source = Input 3	`s output 1 in source 3`	`73 20 6F 75 74 70 75 74 20 31 20 69 6E 20 73 6F 75 72 63 65 20 33 21`
11	Route: Output 1: Source = Input 4	`s output 1 in source 4`	`73 20 6F 75 74 70 75 74 20 31 20 69 6E 20 73 6F 75 72 63 65 20 34 21`
12	Route: Output 2: Source = Input 1	`s output 2 in source 1`	`73 20 6F 75 74 70 75 74 20 32 20 69 6E 20 73 6F 75 72 63 65 20 31 21`
13	Route: Output 2: Source = Input 2	`s output 2 in source 2`	`73 20 6F 75 74 70 75 74 20 32 20 69 6E 20 73 6F 75 72 63 65 20 32 21`
14	Route: Output 2: Source = Input 3	`s output 2 in source 3`	`73 20 6F 75 74 70 75 74 20 32 20 69 6E 20 73 6F 75 72 63 65 20 33 21`
15	Route: Output 2: Source = Input 4	`s output 2 in source 4`	`73 20 6F 75 74 70 75 74 20 32 20 69 6E 20 73 6F 75 72 63 65 20 34 21`
16	Route: Output 3: Source = Input 1	`s output 3 in source 1`	`73 20 6F 75 74 70 75 74 20 33 20 69 6E 20 73 6F 75 72 63 65 20 31 21`
17	Route: Output 3: Source = Input 2	`s output 3 in source 2`	`73 20 6F 75 74 70 75 74 20 33 20 69 6E 20 73 6F 75 72 63 65 20 32 21`
18	Route: Output 3: Source = Input 3	`s output 3 in source 3`	`73 20 6F 75 74 70 75 74 20 33 20 69 6E 20 73 6F 75 72 63 65 20 33 21`
19	Route: Output 3: Source = Input 4	`s output 3 in source 4`	`73 20 6F 75 74 70 75 74 20 33 20 69 6E 20 73 6F 75 72 63 65 20 34 21`
20	Route: Output 4: Source = Input 1	`s output 4 in source 1`	`73 20 6F 75 74 70 75 74 20 34 20 69 6E 20 73 6F 75 72 63 65 20 31 21`
21	Route: Output 4: Source = Input 2	`s output 4 in source 2`	`73 20 6F 75 74 70 75 74 20 34 20 69 6E 20 73 6F 75 72 63 65 20 32 21`
22	Route: Output 4: Source = Input 3	`s output 4 in source 3`	`73 20 6F 75 74 70 75 74 20 34 20 69 6E 20 73 6F 75 72 63 65 20 33 21`
23	Route: Output 4: Source = Input 4	`s output 4 in source 4`	`73 20 6F 75 74 70 75 74 20 34 20 69 6E 20 73 6F 75 72 63 65 20 34 21`
24	Video wall: Wall layout = 2x2	`s tw mode 1`	`73 20 74 77 20 6D 6F 64 65 20 31 21`
25	Video wall: Wall layout = 2x1	`s tw mode 2`	`73 20 74 77 20 6D 6F 64 65 20 32 21`
26	Video wall: Wall layout = 2x1-2	`s tw mode 3`	`73 20 74 77 20 6D 6F 64 65 20 33 21`
27	Video wall: Wall layout = 1x2	`s tw mode 4`	`73 20 74 77 20 6D 6F 64 65 20 34 21`
28	Video wall: Wall layout = 1x2-2	`s tw mode 5`	`73 20 74 77 20 6D 6F 64 65 20 35 21`
29	Video wall: Wall layout = 3x1	`s tw mode 6`	`73 20 74 77 20 6D 6F 64 65 20 36 21`
30	Video wall: Wall layout = 4x1	`s tw mode 7`	`73 20 74 77 20 6D 6F 64 65 20 37 21`
31	Video wall: Wall layout = 1x3	`s tw mode 8`	`73 20 74 77 20 6D 6F 64 65 20 38 21`
32	Video wall: Wall layout = 1x4	`s tw mode 9`	`73 20 74 77 20 6D 6F 64 65 20 39 21`
33	Video wall: All outputs: Wall group source = Input 1	`s tw group 0 input 1`	`73 20 74 77 20 67 72 6F 75 70 20 30 20 69 6E 70 75 74 20 31 21`

34	Video wall: All outputs: Wall group source = Input 2	`s tw group 0 input 2`	`73 20 74 77 20 67 72 6F 75 70 20 30 20 69 6E 70 75 74 20 32 21`
35	Video wall: All outputs: Wall group source = Input 3	`s tw group 0 input 3`	`73 20 74 77 20 67 72 6F 75 70 20 30 20 69 6E 70 75 74 20 33 21`
36	Video wall: All outputs: Wall group source = Input 4	`s tw group 0 input 4`	`73 20 74 77 20 67 72 6F 75 70 20 30 20 69 6E 70 75 74 20 34 21`
37	Video wall: Output 1: Wall group source = Input 1	`s tw group 1 input 1`	`73 20 74 77 20 67 72 6F 75 70 20 31 20 69 6E 70 75 74 20 31 21`
38	Video wall: Output 1: Wall group source = Input 2	`s tw group 1 input 2`	`73 20 74 77 20 67 72 6F 75 70 20 31 20 69 6E 70 75 74 20 32 21`
39	Video wall: Output 1: Wall group source = Input 3	`s tw group 1 input 3`	`73 20 74 77 20 67 72 6F 75 70 20 31 20 69 6E 70 75 74 20 33 21`
40	Video wall: Output 1: Wall group source = Input 4	`s tw group 1 input 4`	`73 20 74 77 20 67 72 6F 75 70 20 31 20 69 6E 70 75 74 20 34 21`
41	Video wall: Output 2: Wall group source = Input 1	`s tw group 2 input 1`	`73 20 74 77 20 67 72 6F 75 70 20 32 20 69 6E 70 75 74 20 31 21`
42	Video wall: Output 2: Wall group source = Input 2	`s tw group 2 input 2`	`73 20 74 77 20 67 72 6F 75 70 20 32 20 69 6E 70 75 74 20 32 21`
43	Video wall: Output 2: Wall group source = Input 3	`s tw group 2 input 3`	`73 20 74 77 20 67 72 6F 75 70 20 32 20 69 6E 70 75 74 20 33 21`
44	Video wall: Output 2: Wall group source = Input 4	`s tw group 2 input 4`	`73 20 74 77 20 67 72 6F 75 70 20 32 20 69 6E 70 75 74 20 34 21`
45	Video wall: Output 3: Wall group source = Input 1	`s tw group 3 input 1`	`73 20 74 77 20 67 72 6F 75 70 20 33 20 69 6E 70 75 74 20 31 21`
46	Video wall: Output 3: Wall group source = Input 2	`s tw group 3 input 2`	`73 20 74 77 20 67 72 6F 75 70 20 33 20 69 6E 70 75 74 20 32 21`
47	Video wall: Output 3: Wall group source = Input 3	`s tw group 3 input 3`	`73 20 74 77 20 67 72 6F 75 70 20 33 20 69 6E 70 75 74 20 33 21`
48	Video wall: Output 3: Wall group source = Input 4	`s tw group 3 input 4`	`73 20 74 77 20 67 72 6F 75 70 20 33 20 69 6E 70 75 74 20 34 21`
49	Video wall: Output 4: Wall group source = Input 1	`s tw group 4 input 1`	`73 20 74 77 20 67 72 6F 75 70 20 34 20 69 6E 70 75 74 20 31 21`
50	Video wall: Output 4: Wall group source = Input 2	`s tw group 4 input 2`	`73 20 74 77 20 67 72 6F 75 70 20 34 20 69 6E 70 75 74 20 32 21`
51	Video wall: Output 4: Wall group source = Input 3	`s tw group 4 input 3`	`73 20 74 77 20 67 72 6F 75 70 20 34 20 69 6E 70 75 74 20 33 21`
52	Video wall: Output 4: Wall group source = Input 4	`s tw group 4 input 4`	`73 20 74 77 20 67 72 6F 75 70 20 34 20 69 6E 70 75 74 20 34 21`
53	Multiview: Multiview layout = Single	`s multiview 1`	`73 20 6D 75 6C 74 69 76 69 65 77 20 31 21`
54	Multiview: Multiview layout = PIP	`s multiview 2`	`73 20 6D 75 6C 74 69 76 69 65 77 20 32 21`
55	Multiview: Multiview layout = Dual	`s multiview 3`	`73 20 6D 75 6C 74 69 76 69 65 77 20 33 21`
56	Multiview: Multiview layout = Triple	`s multiview 4`	`73 20 6D 75 6C 74 69 76 69 65 77 20 34 21`
57	Multiview: Multiview layout = Quad	`s multiview 5`	`73 20 6D 75 6C 74 69 76 69 65 77 20 35 21`
58	Multiview: Multiview layout = User	`s multiview 6`	`73 20 6D 75 6C 74 69 76 69 65 77 20 36 21`
59	Picture: Output 1: Send a picture on	`s output 1 stream 1`	`73 20 6F 75 74 70 75 74 20 31 20 73 74 72 65 61 6D 20 31 21`

60	Picture: Output 1: Send a picture off	`s output 1 stream 0`	`73 20 6F 75 74 70 75 74 20 31 20 73 74 72 65 61 6D 20 30 21`
61	Picture: Output 2: Send a picture on	`s output 2 stream 1`	`73 20 6F 75 74 70 75 74 20 32 20 73 74 72 65 61 6D 20 31 21`
62	Picture: Output 2: Send a picture off	`s output 2 stream 0`	`73 20 6F 75 74 70 75 74 20 32 20 73 74 72 65 61 6D 20 30 21`
63	Picture: Output 3: Send a picture on	`s output 3 stream 1`	`73 20 6F 75 74 70 75 74 20 33 20 73 74 72 65 61 6D 20 31 21`
64	Picture: Output 3: Send a picture off	`s output 3 stream 0`	`73 20 6F 75 74 70 75 74 20 33 20 73 74 72 65 61 6D 20 30 21`
65	Picture: Output 4: Send a picture on	`s output 4 stream 1`	`73 20 6F 75 74 70 75 74 20 34 20 73 74 72 65 61 6D 20 31 21`
66	Picture: Output 4: Send a picture off	`s output 4 stream 0`	`73 20 6F 75 74 70 75 74 20 34 20 73 74 72 65 61 6D 20 30 21`
67	Power: Power On	`s power 1`	`73 20 70 6F 77 65 72 20 31 21`
68	Power: Power Standby	`s power 0`	`73 20 70 6F 77 65 72 20 30 21`
69	Screen: Output 1: Screen on	`s cec hdmi out 1 on`	`73 20 63 65 63 20 68 64 6D 69 20 6F 75 74 20 31 20 6F 6E 21`
70	Screen: Output 1: Screen off	`s cec hdmi out 1 off`	`73 20 63 65 63 20 68 64 6D 69 20 6F 75 74 20 31 20 6F 66 66 21`
71	Screen: Output 2: Screen on	`s cec hdmi out 2 on`	`73 20 63 65 63 20 68 64 6D 69 20 6F 75 74 20 32 20 6F 6E 21`
72	Screen: Output 2: Screen off	`s cec hdmi out 2 off`	`73 20 63 65 63 20 68 64 6D 69 20 6F 75 74 20 32 20 6F 66 66 21`
73	Screen: Output 3: Screen on	`s cec hdmi out 3 on`	`73 20 63 65 63 20 68 64 6D 69 20 6F 75 74 20 33 20 6F 6E 21`
74	Screen: Output 3: Screen off	`s cec hdmi out 3 off`	`73 20 63 65 63 20 68 64 6D 69 20 6F 75 74 20 33 20 6F 66 66 21`
75	Screen: Output 4: Screen on	`s cec hdmi out 4 on`	`73 20 63 65 63 20 68 64 6D 69 20 6F 75 74 20 34 20 6F 6E 21`
76	Screen: Output 4: Screen off	`s cec hdmi out 4 off`	`73 20 63 65 63 20 68 64 6D 69 20 6F 75 74 20 34 20 6F 66 66 21`
77	Presets: Presets 1	`s recall preset 1`	`73 20 72 65 63 61 6C 6C 20 70 72 65 73 65 74 20 31 21`
78	Presets: Presets 2	`s recall preset 2`	`73 20 72 65 63 61 6C 6C 20 70 72 65 73 65 74 20 32 21`
79	Presets: Presets 3	`s recall preset 3`	`73 20 72 65 63 61 6C 6C 20 70 72 65 73 65 74 20 33 21`
80	Presets: Presets 4	`s recall preset 4`	`73 20 72 65 63 61 6C 6C 20 70 72 65 73 65 74 20 34 21`
81	Presets: Presets 5	`s recall preset 5`	`73 20 72 65 63 61 6C 6C 20 70 72 65 73 65 74 20 35 21`
82	Presets: Presets 6	`s recall preset 6`	`73 20 72 65 63 61 6C 6C 20 70 72 65 73 65 74 20 36 21`
83	Presets: Presets 7	`s recall preset 7`	`73 20 72 65 63 61 6C 6C 20 70 72 65 73 65 74 20 37 21`
84	Presets: Presets 8	`s recall preset 8`	`73 20 72 65 63 61 6C 6C 20 70 72 65 73 65 74 20 38 21`

85	**Presets: Save 1**	`s save preset 1`	`73 20 73 61 76 65 20 70 72 65 73 65 74 20 31 21`
86	**Presets: Save 2**	`s save preset 2`	`73 20 73 61 76 65 20 70 72 65 73 65 74 20 32 21`
87	**Presets: Save 3**	`s save preset 3`	`73 20 73 61 76 65 20 70 72 65 73 65 74 20 33 21`
88	**Presets: Save 4**	`s save preset 4`	`73 20 73 61 76 65 20 70 72 65 73 65 74 20 34 21`
89	**Presets: Save 5**	`s save preset 5`	`73 20 73 61 76 65 20 70 72 65 73 65 74 20 35 21`
90	**Presets: Save 6**	`s save preset 6`	`73 20 73 61 76 65 20 70 72 65 73 65 74 20 36 21`
91	**Presets: Save 7**	`s save preset 7`	`73 20 73 61 76 65 20 70 72 65 73 65 74 20 37 21`
92	**Presets: Save 8**	`s save preset 8`	`73 20 73 61 76 65 20 70 72 65 73 65 74 20 38 21`

4. READING THE UNIT BACK

Send these to read the unit back (on a timer, or after a change).

#	String	Bytes (hex)	The reply gives
1	`r output 1 in source`	`72 20 6F 75 74 70 75 74 20 31 20 69 6E 20 73 6F 75 72 63 65 21`	Source
2	`r output 2 in source`	`72 20 6F 75 74 70 75 74 20 32 20 69 6E 20 73 6F 75 72 63 65 21`	Source
3	`r output 3 in source`	`72 20 6F 75 74 70 75 74 20 33 20 69 6E 20 73 6F 75 72 63 65 21`	Source
4	`r output 4 in source`	`72 20 6F 75 74 70 75 74 20 34 20 69 6E 20 73 6F 75 72 63 65 21`	Source
5	`r tw group 0 source`	`72 20 74 77 20 67 72 6F 75 70 20 30 20 73 6F 75 72 63 65 21`	Wall group source
6	`r window 1 in`	`72 20 77 69 6E 64 6F 77 20 31 20 69 6E 21`	windows
7	`r window 2 in`	`72 20 77 69 6E 64 6F 77 20 32 20 69 6E 21`	windows
8	`r window 3 in`	`72 20 77 69 6E 64 6F 77 20 33 20 69 6E 21`	windows
9	`r window 4 in`	`72 20 77 69 6E 64 6F 77 20 34 20 69 6E 21`	windows
10	`r output 1 stream`	`72 20 6F 75 74 70 75 74 20 31 20 73 74 72 65 61 6D 21`	Send a picture
11	`r output 2 stream`	`72 20 6F 75 74 70 75 74 20 32 20 73 74 72 65 61 6D 21`	Send a picture

12	`r output 3 stream`	`72 20 6F 75 74 70 75 74 20 33 20 73 74 72 65 61 6D 21`	Send a picture
13	`r output 4 stream`	`72 20 6F 75 74 70 75 74 20 34 20 73 74 72 65 61 6D 21`	Send a picture
14	`r power`	`72 20 70 6F 77 65 72 21`	Power

5. TROUBLESHOOTING

Nothing happens.
Check the unit's IP address and that TCP 8000 is open between the Tesira server and the unit (same network or VLAN, or routed; no firewall in between). Check the line ending is sent after each string.

The unit answers with an error.
The string or its value is not one it takes, or the unit is in standby: turn it on first.